

DRYCONN[®]

WATERPROOF CONNECTORS

Great for central point connections in low voltage lighting applications



Installation Instructions:

IMPORTANT: Turn off power before installing or removing connector. Product to be used in accordance with local and national codes.

1. Strip conductors.
2. Align any frayed strands or conductors, twist stripped conductors together, and insert into crimp sleeve.
3. Using an indent type crimping tool, crimp sleeve and trim excess bare wire.
4. Insert the splice to the bottom of the sealant filled tube.
5. Position wires into wire channels.
6. Wipe any sealant around opening and conductors.
7. Close lid ensuring latch is secured.

CPC-C (Central Point Connector with Crimps)


Catalog #	Description	Selling Unit
20810	CPC-C	Box of 25

PRODUCT SPECIFICATIONS AND MEASUREMENTS

Max. Voltage: 50V max.
 Connector Size: 3 11/16" x 1 1/2" x 1 3/16"
 Wire Type: Copper/Copper
 Wire Range: Min #18/Max #10
 Temperature Rating: 105°C (221°F)
 Sealant Temperature: -45°F to 400°F
 Tube Construction: Sunlight and Impact Resistant Blended Polypropylene

Measurements (Inches):

- A - 3.67
- B - 1.18
- C - 1.50



Selected 50V Wire Combinations

2 or 3 #10	2, 3, or 4 #12	2, 3, 4, 5, or 6 #14 or #16
2, 3, 4, 5, 6, 7, or 8 #18	1 #10 w/ 1, 2, 3, 4, or 5 #16	1 #10 w/ 1, 2, 3, 4, 5, or 6 #18
2 #10 w/ 1, 2, 3, or 4 #16 or #18	1 #12 w/ 1, 2, 3, 4, or 5 #16	1 #12 w/ 1, 2, 3, 4, 5, or 6 #18
3 #12 w/ 1, 2, or 3 #16 or #18		

Contact factory for a complete list of wire combinations at 800.633.0232.