


Filled Connectors for Outdoor/Electrical Use




INSTALLATION INSTRUCTIONS

IMPORTANT: Turn off power before installing or removing connector. Product to be used in accordance with local and national codes.

- 1. Strip wires 3/4" (19.1 mm).
- 2. Align any frayed strands or conductors.
- Pre-twisting unnecessary. Place stripped wires together with ends of insulation even.
- 4. Twist connector onto wires pushing firmly until hand-tight. Do not over torque.
- 5. Wipe sealant in and around conductors and connector opening while tightening. Do not reuse.





NEC Required for Outdoor Connections

Large Waterproof Connectors

Catalog #	Selling Unit	
62310	Card of 3	
62325	Bag of 15	
62335	Bag of 50	
62340	Bag of 250	

PRODUCT SPECIFICATIONS & MEASUREMENTS

Max. Voltage: 600V max. building wire


(1000V max. signs or luminaires)

Connector Size: 1 1/4" x 13/16" Wire Type: Copper/Copper Wire Range: Min #14/Max #6 Temperature Rating: 105°C (221°F)

UL Designation: LWP*

Measurements (Inches):

A - 1.64 B - 0.82 C - 0.63







UL Listed as a Sealed Wire Connector. For use in dry, damp, wet locations below or above grade when used in an enclosure. For use in direct bury applications when operating at 30 volts or less.

Selected 600V Wire Combinations For use with solid and/or stranded combinations.

2 #8	1 #10 w/3-5 #14	3 #10 w/1-2 #18
2-3 #10	2 #10 w/1-2 #12	4 #12 w/1 #14
3-5 #12	2 #10 w/1-3 #14	1 #10 w/2-3 #12
3 #10 w/1 #14		

Contact factory for a complete list of wire combinations at 800.633.0232.



