

For use with utility tracer lines

### Installation Instructions

IMPORTANT: Turn off power before installing or removing connector. Product to be used in accordance with local and national codes.

- 1. Assemble connection per split bolt manufacturer instructions.
- 2. Lay conductor and connector into housing per Figure 1.
- 3. Close lid of housing, aligning conductors until housing lid is fully latched.
- 4. Do not reuse.




Figure 1

Note: Split bolt size not to exceed 1.0" tall by 0.8" wide by 0.7" deep.

#### MADE IN USA

U.S. Pat. 7,950,956 and additional Patents Pending apply. All other trademarks, U.S. and Foreign Patents Pending apply. All Rights Reserved.

## DryConn® Split Bolt Housing Aqua

| Catalog # | Selling Unit |
|-----------|--------------|
| 69105     | Bag of 10    |

# PRODUCT SPECIFICATIONS & MEASUREMENTS

Max. Voltage: 50V max.

Connector Size: 1.6" deep x 2.9" wide x 1" tall

Wire Range: #14-10 Solid Copper;

#14-10 Steel Core Tracer Wire

Sealant Temperature Rating: -50°C to 200°C

(-58°F to 392°F)

### CONSTRUCTION

Housing: High impact polypropylene

Sealant: Dielectric gel

### **MEASUREMENTS**

A - 1.6"

B - 2.9"

C. 1"

